

Firmware Update With SwemaTerminal 3

The method used to update an instrument's firmware with SwemaTerminal 3 is to have SwemaTerminal 3 send an update command to the connected instrument and then launch a special firmware update program (commands and update program varies with instrument according to UpdateCommands.conf).

To update firmware follow the steps below.

- 1) Connect instrument or Swema sensor via USB to PC
- 2) Start the SwemaTerminal 3 program
- 3) Click on Instrument or sensor name and serial number, then on Update firmware
- 4) An Update program start (instrument displays blink)
- 5) For instruments: In Update program: File-menu → Open User Firmware/Select firmware
For sensors: Select firmware.
Doubleclick firmware that has been downloaded from www.swema.se or com.
- 6) Some lines shows that updating is going on and then that window is closed.
- 7) Detach USB when update done
- 8) Close update program
- 9) Attach USB again
- 10) Restart SwemaTerminal 3 if there is measuring values does not update.
- 11) Verify firmware: Select Terminal. Strike Enter in terminal and view top row.

20210511, CW

www.swema.com

46 8 940090

Pepparv. 27

SE-123 56 Farsta

Sweden